

ATEX Instruction Sheet
Part Number: D803054X012
Publish date: July 2021

Fieldbus H1 Card

KJ3242X1-BA1 Fieldbus H1 Card

Hazardous Atmosphere



II 3G Ex nA IIC Gc
FM12ATEX0090U
IECEX FMG 12.0035U
II 3G EEx nL IIC
Nemko 02ATEX431U

Power Specifications

Local Bus Power	12 VDC at 300 mA
Fieldbus Power	9 to 32 VDC at 12 mA/Port

Environmental Specifications

Ambient Temperature	-40°C to +70°C
Shock	10g ½ Sinewave for 11msec
Vibration	1mm Peak to Peak from 2 to 13.2Hz; 0.7g from 13.2 to 150Hz
Airborne Contaminants	ISA-S71.04 –1985 Airborne Contaminants Class G3
Relative Humidity	5 to 95% Non-Condensing IP 20 Rating
Terminal Block key Position	D6

Note: Refer to the product label for serial number and location and date of manufacture.

Warning: This product has specific instructions for installation, removal and operation in hazardous areas. Refer to document 12P2046 "*DeltaV™ Scalable Process System Zone 2 Installation Instructions*". Other installation instructions are available in the "*DeltaV™ M-Series Hardware Installation and Reference*" manual.

Removal and Insertion

This unit cannot be removed or inserted with system power energized unless the area is known to be non-hazardous and only one unit at a time may be removed or inserted.

Non-sparking field circuits **MUST** be de-energized before removing and inserting.

For "nL" installation, an I/O loop assessment must be completed on all energy-limited nodes.

A rotary keying system ensures compatibility between I/O cards and terminal blocks after installation is complete. The terminal block must have the keys set for the I/O card with which it is used.

Maintenance and Adjustment

This unit contains no user serviceable parts and should not be disassembled for any reason. Calibration is not required.

Other Safety Approvals



Emerson Automation Solutions
Round Rock, Texas





GLOBAL INDUSTRIAL AUTOMATION SOURCING

Ready to source this part?

Ask for availability, pricing and delivery options.

Request a fast quote

Include the product title and any required part number or quantity.

EMAIL

info@apterpower.com

PHONE

+86 18106909650

CHAT ON WHATSAPP >



SCAN TO CHAT ON WHATSAPP

PRODUCT: KJ3242X1-BA1 / DeltaV M-series FOUNDATION Fieldbus H1 Card

The enclosed manufacturer pages are reproduced without alteration to technical content.

Apter Power is not an authorized distributor, reseller or representative of the products featured.

Product names, trademarks, brands and logos remain the property of their respective owners.